

DN-X120

2-channel Desktop DJ-Mixer



Extremely compact
DENON build quality

2CH Battle style
Quality

Cross Fader Reverse
Designed for DN-S1200 sets

2 channel DJ-Mixer, desktop

Line Input 4 x (LINE 1, 2, 3, 4)

PHONO-IN 2 x selectable (PHONO 1/CH 1 & PHONO 2/CH 2)

Gain control

All input channel levels can be pre-adjusted to match the output level meter ensuring a smooth transition between fades.

Mic-IN

1 x MONO ¼-TRS (6,3mm), connector on backside with level control, 2 Band EQ+ Mic Talkover Switch

3 Band EQ with full kill

Channel 3 Band EQ

HI -40dB to +10dB

MID -40dB to +10dB

LOW -40dB to + 6dB

Output

balanced L/R STEREO, 2 x ¼-TRS (6,3mm)

unbalanced L/R STEREO, 2 x RCA (Cinch)

Split Cue

headphone output selector, ¼-TRS (6,3mm) on frontside

45mm VCA Cross Fader

Contour level/reverse switch

Cross Fader Start switchable

Fader Start terminal

10 segments Level Meter

Backlit DENON DJ logo

Simple & easy operation

External power supply

Dimensions: 215 (W) x 87,4 (H) x 232 (D) mm
(without feet & jogdisc)

The Ultimate Performance Package

1x DN-X120 & 2x DN-S1200



Design and specifications are subject to change without notice.



DN-B01BK: optional carrying bag
for 2x DN-S1200 & 1x DN-X120